

# PC1021MII Main/Standby Amplifier Auto Switcher



## Features

- Can automatically detect audio amplifier failure and switch between “main amplifier” and “standby amplifier” .
- With 4 identical independent channels, each channel can support automatic detection and switching of the main/standby amplifier.
- With manual selection of main / standby amplifier.
- Support PC remote monitoring.

## Specification

Controllable Channel Groups	4 groups
Channel Working Capacity	150V/10A (audio signal)
Amplifier Gain	>20dB
Input Detection Threshold	<100mV
Channel Detection Time	20ms
Power	AC220V/50Hz
Protection	F1AL
Package Dimensions	(L×W×H) 555×455×185
Machine Dimensions	(L×W×H) 484×320×88
Gross Weight	7.8kg
Net Weight	6.2kg